## HƯỚNG DẪN DÙNG PHẦN MỀM CHÉP FILE CHO FV-200EV

- I. Hướng dẫn download, cài đặt và chép file vào FV-200EV.
- 1. Download phần mềm phiên bản 5.0 <u>ở đây</u>.
- 2. Cài đặt phần mềm lên máy tính. Yêu cầu máy tính cài đặt Windows XP
- 3. Cắm cáp USB nối FV-200EV với máy tính.
- 4. Cài đặt Driver cho thiết bị FV-200EV.

Driver nằm trong thư mục của phần mềm download về.



Sau khi cài đặt Driver nếu giao diện Device Manager của Windows nhân được Driver như trên là được.

5. Chạy phần mềm ta có giao diện sau:

) Edit(E) View											
Sound Repeater Control PLAY REC STOP	Memory Information - Project name FS7000EV"r Explanation	í•ú'—	Creator		Model © EV-20R © PM-20EV © EV-20A © EV-20S © S-20S		PC HDD Informati Project na Explanatic	on ame	Creator		Model © EV-20R © PM-20EV © EV-20A © EV-20S © S-20S
Format	Read	Write	Clear	Refrest	Connect	<<	Enter	Delete	Open	Save	Link wave files
	Filename	Size KByte	Size Sec C	Comment	Interval	>>	Filename	Size KByt	Size e Sec	Comment	Interval
No.1: •	(no file)	0	0		(no repe; =			<u> </u>			(no repet -
No.2: C	BGM_0001.W	5106	60		(no repe; 🔻			— i —		( <u> </u>	(no repe: *
No.3: C	BGM_0002.W	4772	56		(no repe; *					1	(no repei -
No.4: C	(no file)	0	0		(no repe; *						(no repei
	Free space	6336	73				Free s	pace 1624	40 188		
20R Wave file auditio (No Disk)	n.				Select folder Start audition Stop audition			So	лт	d Rep	peater

6. Nhấn vào nút "Connect" trên phần mềm

🧀 🔛   🐰 🖻	<b>B</b> ?											
Sound Repeater	Memory					-	PC HDD					
Control	Information -	6				-	Informati	on —	120.00	5 <sup>1</sup>		
DIAV	Project name	(ef)	Creator	<u>[</u>			Project na	ame	Creator	0	Model	
FLAT	Explanation	1 - U	1		C DM.20EV		Explanation C pi					
🔶 REC				C EV-20A						C EV-20A		
STOP					C EV-205						C EV-20S	
					C S-205	1					C 5-205	
Format	L.						Ľ					
	Read	Write	Clea	ar Refr	esh Connect	>>	Enter	Delete	Open	Save	Link wave file:	
	Filename	Size KByte	Size Sec	Comment	Interval		Filename	Size KByt	Size se Sec	Comment	Interval	
No.1: 🔎	(no file)	0	0		(no repei						(no repei	
No.2: C	BGM_0001.W	5106	60		(no repei						(no repe;	
No.3: C	BGM_0002.W	4772	56		(no repe:						(no reper	
No.4: C	(no file)	0	0		(no repei						(no repei	
	Free space	6336	73				Free s	pace 162	40 188	1		
-20R												
Wave file audition	n.											
(No Disk)					Select folder							
1								C		10		
				Start audition			Sound Repeater					
					Stop audition							

## 7. Chép file evacuation:

Sound Repeater	Memory				i i	PC HDD	ion			
PLAY	Project name Creator			C PM-20EV		Project r Explanat	name Creator			Model     EV-20R     PM-20EV
REC     STOP		2		C EV-20A C EV-20S C S-20S						C EV-20A C EV-20S C S-20S
Formac	Read W	rite Cle	ar EV20man	al const		×	Delete	Open	Save	Link wave files
	Filename K	e Size	C				Size	Size	Comment	Interval
No.1: C	(no file) 0		П 🔺	Delete file 'KASAL	2.WAV'.	OK?			[	(no repei *
No.2:	KASAI2.WAV 2	599 31	1		5		-i-		[	(no repei -
No.3: C	BGM_0002.W 4	772 56			1					(no repe; -
No.4: C	(no file) 0	0		Yes		No				(no repe; *
20R	Free space 8	864  102					space   1624	0   188		
Wave file auditio	n				1					
(No Disk)				Select folder						
							Se	HIM	L Ret	peater
				Start audition			00		- Imp	

**Bước 1:** Chọn vào "No.2" sao cho dấu chấm đen chọn về đó là được. **Bước 2:** Chọn vào nút "Write".

Bước 3: Chọn vào "Yes" nếu có.

Sound Repeater Memory	ation			PC H	DD ormation			
PLAY PTC FS PLAY PTC FS PTC FS PT	Copen Look in: Recent Places Desktop Libraries Computer	Desktop File Shc Shc Shc Shc 1.00 Đặt 1.1' Shc 1.1' Shc 1.0' Hik Wa Wa	folder o giá ortcut 5 KB ortcut 5 KB ogle Drive ortcut 0 KB (ASA3 ve Sound 9 MB		- 🗈 💣 🆽		re	Model           © EV-20R           © PM-20EV           © EV-20A           © EV-20S           © S-20S   Interval Inte
-20R Wave file audition. (No Disk)	Network	File name: Files of type:	SAI2 ve Sound 3 MB KASAI2 WAV(*.WAV) Start audition Stop audition		•	Open Cancel	Repe	eater

F) Edit(E) View(V) Help(H)			
🚔 🖬   X 🖻 🛍   🎖			
Sound Repeater Memory		PC HDD	
Control Information	Madal	Information Brainst pages - Craster	Madal
ES7000EV"ñi•ii'-		Project name Creator	- Model
Explanation		Explanation	C PM-20EV
REC	C EV-204		C EV-20A
	C EV.205		C EV-205
	C 5-205		C 5-205
Format	<		
Read Write EV2	0man	te Open Save	Link wave file
Filename KByte	-	KByte Sec Commer	nt Interval
No.1: C (no file) 0	Write file 'KASAI2.WAV'?		(no repe;
No 2: @ KASAT2 WAV 2599			(no repe
No 2: C RCM 0002 W 4772			(no reper
No.5. (BBM_0002.VV  4772 ]	Ves No	Cancel	(no repe
No.4: ( (no file) 0		concor	(no repei
Free space 8864		16240 188	
200			
206			
Wave file audition.			
(No Disk)	Select folder		
		Sound R	phoator
	Start audition	Source ra	penner
	Stop audition		
1			

Bước 4: Chọn đến File nhạc cần chép rồi chọn "Open".

Bước 5: Chọn "Yes" để ghi file Evacuation mới vào.

Sound Repeater Control PLAY REC	Memory Information - Project name FS7000EV"A Explanation	lí•ú'—	Creator		Model C EV-20R C PM-20EV C EV-20A C EV-20A		PC HDD Information Project name Explanation	Creator		Model © EV-20R © PM-20EV © EV-20A © EV-20S
Format					Sound Repea	ter		×		○ S-20S
No.1: ( No.2: ( No.3: ( No.4: (	Read Filename (no file) KASAI2.WAV BGM_0002.W (no file) Free space	Write Size KByte 0 2599 4772 0 8864	Clear Size Sec 0 31 56 0 102	r <u>Refr</u> Comment	Writing	KASAI2	.WAV	Cancel	nt	Interval (no repei (no repei (no repei (no repei
-20R Wave file audition	n.—					]				
(NO DISK)					Select folder			Sound	Rep	eater

**Bước 6:** Chờ quá trình ghi hoàn tất, ta đã chép được file Evacuation mới vào FV-200EV

## 8. Ghi file False Alarm mới vào FV-200EV

Bước 1: Thao tác giống bước 1 ở trên chỉ chọn lại là vị trí cần ghi là "No.3" Bước 2 đến bước 6 thao tác giống như trên

- II. Thông số file nhạc chép vào:
  - 1. File nhạc chép vào có định dạng là file WAV.
  - 2. Tên file chép vào không sử dụng tiếng việt, không để dấu cách và có độ dài không quá 8 ký tự.
  - 3. Thông số file way này cần:
    - Sampling Frequency: 44100Hz.
    - Quantifying Number: 16bits.
    - Mode: Mono
    - Data format: PCM.
    - Filename: 8.3 format (Up to 8 alphanumberic/ underbar)
    - Extention: WAV.
    - Format: Wave format.